

ER26xx Service

多功能電子手輪 (多功能手動脈衝發生器)

Handy Manual Pulse Generator

特點:

- ★波段開關最多可達12軸
- ★高性能可搭配2個功能開關和一個緊急停止開關
- ★極簡外型, 輕便符合人體工學
- ★零件均採用日本技術零件
- ★外殼採用高強材料耐衝擊
- ★連接線使用屏蔽編織網信號傳輸線抗干擾
- ★進口PU外皮耐磨耐油水
- ★手輪背後附強力磁鐵
- ★可另選配掛鉤, 安裝方便
- ★外殼面板可客製Logo, 獨具特色

FEAURES:

- ★ Rotary switch steps 1-11 axis
- ★ High performance offers 2 function openings and 1 emergency stop opening
- ★ Magnetic back cover
- ★ Dust & Water proof (IP65)
- ★ Optimal solution
- ★ Multiple output types compatible with different CNC control systems



ER26xx-BT-MKx-S-xx

配號	電源 DC Power	脈波 PULSE	輸出 Signal Mode
267	5V	100PPR	AB
2671	5V	25PPR	AB
268	12V	25PPR	AB
2681	12V	100PPR	AB
269	5V Line Drive	100PPR	A,B/A,B'
2691	5V Line Drive	25PPR	A,B/A,B'
250	24V	25PPR	AB
251	24V	100PPR	AB

B	標準型
F	功能型

外型	選配		
	致能開關	致能開關	緊急停止
T			
C	●		
D	●	●	
E			●
F	●		●
G	●	●	●

Model Number	Rotary Switch Steps
MK 1	PTP 1 串由
2	2 AXIS
3	3 AXIS
4	4 AXIS
5	5 AXIS
6	6 AXIS
H	7 AXIS
J	8 AXIS
K	9 AXIS
D	10 AXIS
M	11 AXIS
MB A	BIN 3 AXIS
B	BIN 4 AXIS
C	BIN 5 AXIS
D	BIN 6 AXIS
E	BIN 7 AXIS
F	BIN 8 AXIS
G	BIN 9 AXIS
H	BIN 10 AXIS
I	BIN 11 AXIS

特殊記號

Cable	
S	3m
L	5m